

Mixer y Switchers

Switcher HD de 6 entradas rackeable**SE-1200MU**

Video Standard	HD
Video Format	1080i 50/59.94/60Hz 720p 50/59.94/60Hz
Video Processing	SDI: 4:2:2 HDMI: YUV 4:2:2 10 bit, RGB 4:4:4
Input Routable / Crosspoint	All 6, repeatable
Video Input	4x HD-SDI 2x HDMI (RGB/YUV, 1080i/1080p/720p)
Mix HD & SD Source	----
Computer Graphic Interface	2 via HDMI
Video Output	2x HD-SDI 2x HDMI assignable: PGM(w/DSK 1&2), PGM(w/DSK 1), PGM Clean, PVW(w/o DSK), multi-view, Input 1-6
Down-converted Output	----
Built-in Multi-view Monitoring Out	HDMI & SDI assignable, Ethernet (MJPEG)
Analogue Audio Input	2x Balanced XLR
Analogue Audio Output	----
Digital Embedded Audio Support	Input 2 channels, Output 2 channels
Audio Delay Calibration	----
A+V Switching	Yes
Chromakey	2
Title Creator	----
USK	2x Keyer support Chromakey/ Linear/ Luma Key
DSK	2x DSK support Lumakey/ Linear key (Key / Fill)
Picture in Picture	1
Logo Insertion	----
Still Store	500
Effects	FTB, Cut, 32 Wipe with border
Transition Preview	Full transitions preview
Sync / Reference In/Out	Built-in Genlock (internal)
Tally Output	1x D-sub 15pin, dual color
PC Remote Control	Ethernet (free Window software) RS-422/ RS-232
Built-in Audio Mixer	----

Special Features	Motion JPEG Multi-view streaming (120 memory preset, BGD Transition on/off option) Free Virtual Set and Stinger transition included
Chassis	1RU rack-mount mainframe
Dimension (LxWxH)	440 x 215 x 49 mm
Weight	1.5 kg
Power	DC 12V, 19W
Operating Temp. Range	0~40 °C
What's in the Box	1 x SE-1200MU product 1 x AD Switch DC 12V 1 x DB9P TO DB9P Cable 2 x 1U Rack Mount Ear 6 x M4 Screws for Rack Mount Ear