Camera Control

# Multi Camera Control Unit for BC-100 Camera

**MCU-400**

| | |
|---|---|
| Camera Input | ---- |
| Camera Side Adapter | ---- |
| Camera Controlled Qty | 4 |
| CAM Remote Interface | RS-422 (RJ-45 Port) x 4<br>DVIP (RJ-45 Port) x 1 |
| Video Input | ---- |
| Video Output | ---- |
| Composition Monitoring to View the Camera's own LCD/OSD menus | ---- |
| Support Functions | Camera User memory functions<br>Camera OSD Menu Navigation<br>Shutter adjustment<br>Iris adjustment<br>White Balance functions<br>Camera Gain adjustment |
| Compatible Camera Models | Datavideo BC-100 |
| Connection Distance | 100m |
| Dimension (LxWxH) | 440 x 125 x 44 mm |
| Weight | 1.8 kg |
| Operating Temp. Range | 0~40 °C |
| Power Transmission | ---- |
| Power | DC 12V, 1A |
| What's in the Box | 1 x MCU-400 Product<br>1 x AD Switch DC 12V<br>1 x Ethernet Cable<br>2 x Ear mount kit<br>4 x M4 x 8mm screws<br>4 x M5 x 10mm screws |