

Mélangeurs audio

Mélangeur audio
AM-100

Audio Input	6x XLR (4 for Line-in/Mic-in adjustable)
Audio Output	2x XLR
Audio Indicator	Audio Level LED
Audio Delay	----
Audio Sample Rates	---
Special Feature	Tally Signal Output, A+V
Chassis	Rack-mountable with RMK-1 Rackmount Kit
Power	DC 12V 30W
Dimension (LxWxH)	482 x 112 x 41 mm
Weight	1.8 kg
Operating Temp. Range	0~40 °C
What's in the Box	1 x AM-100 Audio Mixer 1 x AC Cord 1 x AD Switch DC 12V / 2.5A